



A stylish exit sign or wall luminaire for prestigious interior applications

Kea stylish appearance coupled with it's distinctive symmetrical design makes it ideal for the most prestigious applications.

Suitable as an exit sign or a high frequency mains/emergency luminaire, Kea is available in



Options Suffix:

opeio	iis sairiik.		
/AD	Intelligent Addressable	/ST	Digital Self-Test
	Luminaire	/SG	Silver Grey
/FX	Exit Fascia		Finish

Mains Luminaires

Cat No.	Mode/Lamp	Lumens	Kg
KE14	14W T5 HF Mains		3.20
KE36	36W TC-L HF Mains		3.30

Emergency Luminaires

Cat No.	Mode/Lamp	Lumens*	Kg
KE14/M3	14W T5 M3 Emergency	384	4.20
KE36/M3	36W TC-L M3 Emergency	435	4.20

Slave Luminaires

Cat No.	Mode/Lamp	Lumens*	Kg
KE14/#D	14W T5 Slave Emergency	384	3.20
KE36/#D	36W TC-L Slave Emergency	435	3.30

^{*} Emergency Lumens

Replace # with AC/DC 24, 50, 110 or 230 system Voltage

 * For other durations, specify the required time period e.g. /M3 but for 1 hour duration becomes /M1

Dimensions: 610mm Length x 200mm Width x 105mm Depth

