

## INSTALLATION INSTRUCTIONS



## TRIDENT LEDLITE




## **Important Safety**

1. Before installation or maintenance, ensure that the mains supply to the luminaire is switched off and circuit supply fuses are removed or the circuit breaker is turned off.
2. It is recommended that only a qualified electrical contractor carries out the installation of this luminaire and that the luminaire is installed in compliance with the current edition of the IEE wiring Regulations.
3. The person carrying out the installation is to check and verify that the total load on the circuit, including that of this luminaire does not exceed the rating of the circuit cable, fuse or circuit breaker.
4. Where applicable, careful consideration should be taken during installation to ensure that all fixings and/or suspensions are of a suitable size for the luminaire being installed.


### **INSTALLATION DIAGRAMS**

1. Mark the locations of where the fitting is to be placed, then drill 6mm holes for the brackets.
2. Insert the expansion plug into the holes drilled and fix the brackets using the screws.
3. Clip the body of the fitting to the brackets in the correct positions and insert the supply cable through the compression gland.




4. Raise the LED tray to the body and attach the supply cable into the terminal block on the back of the LED tray, tighten the compression gland and then clip the LED tray into the body.

Standard



Emergency



5. Place the diffuser into the body and ensure all the diffuser clips are clipped into place and seated correctly.
6. Turn the power back on to the circuit being worked on and make sure the fitting is working correctly.





Telephone: +44 (0)1704 512000  
Email: [info@morganhope.com](mailto:info@morganhope.com) [www.morganhope.com](http://www.morganhope.com)